



OPTIONS

Ballast Covers	-BC (contact factory)
Flex Conduit	-FX (please specific length)
Auto Test	- AT -luce-3, luce-4, luce-7

LUCE PLUS

If you are unable to locate the specific LUCE model to meet your requirements; please contact Beghelli USA Customer Service at 1-800-723-4316. Additional LUCE series products are available upon request. Proper specifications are required.

INSTALLATION

The LUCE series is suitable for new build and retrofit installations. Indoor, cold temperature and damp location models are available to be configured for installation on normally inflammable surfaces.

LUCE - Emergency ballast

The LUCE series of emergency ballasts are designed to provide emergency illumination capability to existing or new fluorescent fixtures. LUCE series products consist of an internal nickel cadmium battery, charger and electronic circuit. A durable steel housing contains all components of the LUCE series. The LUCE series is available from 500 - 3000 lumens. The LUCE series is available for indoor, cold temperature, and damp location installations. Please consult Beghelli USA Customer Service for accurate installation specifications when ordering.

DIMENSIONS

Series	A	B	C
LUCE-1	9.4"	2.4"	1.5"
LUCE-2	9.4"	2.4"	1.5"
LUCE-3	13.3"	2.4"	1.5"
LUCE-4	16.3"	5.5"	1.7"
LUCE-5	9.5"	2.375"	1.5"
LUCE-6	9.5"	2.375"	1.5"
LUCE-7	9.5"	2.375"	1.5"
LUCE-8	17.5"	1.18"	1.15"
LUCE-9	21.5"	1.18"	1.15"

DIMENSIONS

Model	Lumens	# Lamps	Description
LUCE-1	500	1	2'-4' single, bi-pin T8-T12 linear fluorescent
LUCE-2	700	1, 2	2'-8' single, bi-pin T8-T12 linear fluorescent 2'-4' double, bi-pin T8-T12 linear fluorescent
LUCE-3	1400	1, 2	2'-8' single, bi-pin T8-T12 linear fluorescent 2'-4' double, bi-pin T8-T12 linear fluorescent
LUCE-4	3000	1, 2	2'-8' single, bi-pin T8-T12 linear fluorescent 2'-4' double, bi-pin T8-T12 linear fluorescent
LUCE-5	650	1, 2	7, 9, 12w twin tube, 2 pin CF 9-13w quad tube, 2 pin CF
LUCE-6	650	1	18-26w quad tube, 2 pin CF
LUCE-7	650	1	10-42w 4 pin rapid start CF
LUCE-8	825	1	2'-4' T5-T5HO linear, 40-55w 4 pin CF
LUCE-9	1300	1	2'-4' T5-T5HO linear, 40-55w 4 pin CF

EXAMPLE: LUCE-3
DESCRIPTION: LUCE emergency ballast, 1400 lumens.

WARRANTY

The LUCE Series comes with a 5-year factory warranty. Deliberate damage, misuse, improper installation effectively cancel the warranty.